

Ashok Sales, 210, New Raviwar path,
Near Fulwala Chowk,
Pune-411002.
Ph:- 020-24471041
MOB:- 9764715150
E-Mail :- tusharshah@ashoksales.com
Website:- ashoksels.com

Conductivity Chart of Copper Bus Bar

Size(mm)				A C No of Buses			D C No Of Buses		
	Cross Sectional Area in MM	1	2	3	4	1	2	3	4
		I	II	III	II50II	I	II	III	II50II
12x2	23.5	110	200			115	205		
15x2	29.5	140	200			145	245		
15x3	44.5	170	300			175	305		
20x2	39.5	185	315			190	325		
20x3	59.5	220	380			225	390		
20x5	99.1	295	500			300	510		
25x3	74.5	270	460			275	470		
25x5	124	350	600			355	610		
30x3	89.5	315	540			320	560		
30x5	149	400	700			410	720		
40x3	119	420	710			430	740		
40x5	199	520	900			530	930		
40x10	399	760	1350	1850	2500	770	1400	2000	
50x5	249	630	1100	1650	2100	650	1150	1750	
50x10	499	920	1600	2250	3000	960	1700	2500	
60x5	299	760	1250	1760	2400	780	1300	1900	2500
60x10	599	1060	1900	2600	3500	1100	2000	2800	3600
80x5	399	970	1700	2300	3000	1000	1800	2500	3200
80x10	799	1380	2300	3100	4200	1450	2600	3700	4800
100x5	499	1200	2050	2850	3500	1250	2250	3150	4050
100x10	999	1700	2800	3650	5000	1800	3200	4500	5800
120x10	1200	2000	3100	4100	5700	2150	3700	5200	6700
160x10	1600	2500	3900	5300	7300	2800	4800	6900	9000
200x10	2000	3000	4750	6350	8800	3400	6000	8500	10000